

## CCD B/W Video Camera Module XC-ST30/CE XC-ST50/CE XC-ST51/CE XC-ST70/CE

The XC-ST Series cameras incorporate the innovative CCD and signal processing technologies into a compact black and white camera module. A new external trigger design allows the electronic shutter speed to be freely specified by the width of an external trigger pulse or by a switch setting on the rear panel of the camera. These cameras are also user-friendly, with all switch settings located on the rear panel.

Moreover, the 1/3 type CCD, 1/2 type CCD and 2/3 type CCD models have the exact same dimensions, simplifying space requirements and making it easy to interchange them if necessary. These features, along with high picture quality and high shock and vibration tolerance make the XC-ST Series cameras ideal for demanding machine vision applications.


## **Features**

- XC-ST30/CE: 1/3 type IT CCD
- ▲ XC-ST50/CE: 1/2 type IT CCD
- ▲ XC-ST51/CE: 1/2 type IT CCD
- XC-ST70/CE: 2/3 type IT CCD
- Small and lightweight: 44 (W) x 29 (H) x 57.5 (D) mm, 110 g (XC-ST70/CE is 105 g)
- High sensitivity: 0.3 k (F1.4) (XC-ST51/CE has sensitivity of 0.2 k at F1.4)
- High S/N ratio: 54 dB (XC-ST30CE), 58 dB (XC-ST50CE, XC-ST51CE and XC-ST70CE)
- Electronic shutter function (1/100 to 1/10,000 s)
- Flexible trigger shutter functions


   simple trigger with internally generated HD/VD and Write Enable (WEN)
   exposure control with switches or trigger pulse width
- Readout on command (with HD/VD input)
- 2:1 interlace
- Frame/field exposure
- Restart/Reset mode
- Synchronisation: internal/external (HD/VD, VS)
- High shock and vibration tolerance




Connections



## Locations of Parts & Operations





#### 12 pin multi-connector

Pin No.	Internal HD/VD sync	External HD/VD sync	External C. sync	
1	GND	GND	GND	
2	+12 V	+12 V	+12 V	
3	GND	GND	GND	
4	VIDEO output	VIDEO output	VIDEO output	
5	GND	GND	GND	
6	Internal HD output	External HD input	—	
7	Internal VD output	" External VD input	VS input	
8	GND	GND	GND	
9	—	—	—	
10	<sup>*4</sup> WEN output	<sup>-4</sup> WEN output	<sup>*4</sup> WEN output	
11	TRIG input	TRIG input	TRIG input	
12	GND	GND	GND	

<sup>13</sup>: In Restart/Reset mode VD input is necessary <sup>14</sup>: WEN output is only effective in EXT trigger shutter mode

#### Lens mount (C mount) A commercial C mount lens as well as Sony standard lenses can be used.

- 2 Camera fixing reference hole High-precision screw hole machined on the lens mount surface.
- Screw hole for tripod adaptor installation (VCT-ST70I)
- 12 pin multi-connector The 12 pin multi-connector is connected to a DC IN/SYNC (DC power/sync signal input)
- BNC connector Video out
- G Gamma correction ON/OFF switchable
- Internal/External synchronisation switch In the EXT position, if there is no external sync input, the internal sync is activated inside the camera. In this case, HD/VD signal is not output through the 12 pin multi-connector.

- Trigger polarity switch The trigger polarity is selectable (neg/pos polarity)
- 9 75 Ω termination switch
   0 Dip switch

Dip switch 1 - 4: Shutter speed Dip switch 5: FRAME/FIELD exposure Dip switch 6 - 8: Normal shutter mode, External trigger shutter mode, Restart/ Reset mode

#### Gain switch

A: Image output at a fixed level of image according to the brightness of the subject. (Variable range: 0 to 18 dB) F: Fixed gain 0 dB M: gain (manual) Factory setting: the variable gain is adjusted to the fixed sensitivity for a standard subject. When using two or more XC-ST30/CE, XC-ST50/CE, XC-ST51/CE or XC-ST70/CE cameras, identical images of the same subject can be attained.

12 Gain control

The gain can be adjusted between 0 to 18 dB when the gain switch is set to "M".

#### Rear panel factory settings

No.	Switch	Factory setting
6	Gamma correction ON/OFF	OFF
0	Internal/External sync	EXT
8	Trigger polarity	+
9	75 $\Omega$ termination	ON
10	Dip switch	
	1 · 2 · 3 · 4: Shutter speed	OFF
	5: Field/Frame	OFF
	6 · 7 · 8: normal shutter/EXT trigger shutter/restart reset	OFF
0	GAIN	FIX





multi-connector


## **Trigger Shutter Modes**

A new external trigger design allows the electronic shutter speed to be freely specified by the width of an external trigger pulse or by a switch setting on the rear panel of the camera.

## Shutter speed setting based on the trigger width







\* When switching from Ext. trigger to regular operation the WEN pulse is output


#### Shutter speed settings by dip switch control

Shutter speeds are set by dip switches 6, 7, 8, on the camera's rear panel. The width of the trigger pulse is irrelevant.

# **XC-ST Series**

	XC-ST30	XC-ST50	XC-ST51	XC-ST70	XC-ST30CE	XC-ST50CE	XC-ST51CE	XC-ST70CE
Image device	1/3 type IT CCD	1/2 type IT CCD	1/2 type IT CCD	2/3 type IT CCD	1/3 type IT CCD	1/2 type IT CCD	1/2 type IT CCD	2/3 type IT CCD
Effective pictures								
elements		768 (H) :	< 494 (V)		752 (H) × 582 (V)			
Signal system		EIA sta	andard			CCIR st	andard	
Horizontal frequency	15.734 kHz ±1%				15.625 kHz ±1%			
Vertical frequency		59.9	4 Hz			50	Hz	
Lens mount	C mount							
Flange back				17.52	'6 mm			
Sync system				Internal / E>	ternal (auto)			
External Sync system				HD / VD (2	~ 5 Vp-p), VS			
External Sync frequency				Horizontal s	ync frequency ± 1%			
Jitter	less than ± 50 nsec							
Scanning system	525 lines, 60 fields/s, 2:1 Interlaced					625 lines, 50 field	s/s, 2:1 Interlaced	
Video output	1.0 Vp-p, negative, 75 $\Omega$ unbalanced							
Horizontal resolution	570 TV lines					560 T\	/ lines	
Sensitivity	400 lx, F5.6	400 lx, F8	400 lx, F11	400 lx, F8	400 lx, F5.6	400 lx, F8	400 lx, F11	400 lx, F8
(y compensation ON, 0 dB)								
Minimum illumination (F1.4,	0.3 lx 0.2 lx 0.3 lx			0.3 lx	0.3 lx 0.2 lx 0.3 lx			0.3 lx
AGC ON, without IR cut filter)								
S/N ratio	56 dB		60 dB		54 dB 58 dB			
Gain	AGC (0 ~18 dB) / Manual (0 ~18 dB) / Fixed (0 dB) Selectable							
Gamma	ON / OFF							
Normal shutter		1/100 ~ 1	/10,000 s			1/120 ~ 1	/10,000 s	
External trigger shutter	1/4 ~ 1/10,000 s			1/4 ~ 1/8,000 s				
Power requirements	DC 12 V ±10%							
Power consumption	1.9 W 2.0 W 2.1 W		2.1 W	1.9 W 2.0 W			2.1 W	
Dimensions				44 (W) x 29 (H	) x 57.5 (D) mm			
Mass		110 g		105 g		110 g		105 g
Operation temp. / Humidity				-5°C ~ +45°(	C / 20 ~ 80%			
Storage temp. / Humidity	-30°C ~ +60°C / 20 ~ 95%							
Vibration	10 G (20 ~ 200 Hz)							
Shock resistance	70 G							
MTBF	70,600 hrs.							
Regulations	UL6500, FCC Class B, IC Class B, CE (EN61326/97 + A1/98), AS4251.1 + AS4252.2							
Supplied accessories				Lens mount cap (x 1), 0	perating instructions (x 1	)		
Optional accessories	DC-700CE: Compact camera adaptor (CE standard): Compact, lightweight, Two video outputs, External sync IN/OUT,							
	Trigger input/WEN output, New EIAJ standard 12 pin assignment, Dimensions: 110 (W) x 53 (H) x 160 (D) mm							
	CCXC-12P02N (2 m), CCXC-12P05N (5 m), CCXC-12P10N (10 m), CCXC-12P25N (25 m): 12 pin camera cable (CE standard)							
			VCT-ST70I: Tripod ada	ptor: Isolated type, Approx	k. 14 g, Dimensions: 40 (	W) x 6 (H) x 59 (D) mm		

## Dimensions



ISS for Central Zone	+49 221 537 3668
(Austria, Eastern Europe, Germany, Netherlands, German-speaking Switzerland)	
ISS for Nordic Zone	+45 43 557 067
(Baltics, Denmark, Finland, Norway, Sweden)	
ISS for Other Zone	+44 1932 816 315
(UK, Ireland, Greece, Israel, South Africa)	
ISS for South Zone	+33 1 55 90 40 74
(Belgium, France, Portugal, Spain, French-speaking Switzerland)	
ISS for Italy	+39 (0) 6 334 372 27